



## PATL-105

Order No.: 1000266

### PRODUCTINFOS

#### 5-way 100 V transformer,

for connecting a 100 V audio signal source to devices with line inputs.

- Suitable for PA mixing amplifiers PA-1120, PA-1240, PA-6240, PA-6480, PA-6000
- Transforming 100 V output signals into line signals to 5 lines (galvanically isolated)
- To be mounted directly to the rear panel of a respective amplifier
- Frequency range: 15-30,000 Hz
- Dimensions: 120 x 75 x 60 mm
- Weight: 405 g

#### Manufacturer information:

MONACOR INTERNATIONAL GmbH & Co. KG  
Konsul-Smidt-Str. 68  
28217 Bremen  
Germany  
info@monacor.com

## Safety Notes and Warning Messages

During operation, there is a hazard of contact with a voltage of up to 100 V at the connection cables. Installation must be carried out by skilled personnel only.

The unit is suitable for indoor use only. Protect it against dripping water and splash water, high air humidity and heat (admissible ambient temperature range: 0 - 40 °C).

If the unit is to be put out of operation permanently, take it to a local recycling plant for a disposal which is not harmful to the environment.

## TECHNICAL SPECIFICATIONS

### PATL-105

Description	100 V transformer
Frequency range	15-30,000 Hz
Input impedance	20 kΩ
Output impedance	200 Ω
Admiss. ambient temp.	0-40 °C
Dimensions	120 x 75 x 60 mm
Weight	405 g
Inputs	cable lugs
Outputs	screw terminals

### PATL-105

EAN code	4007754277012
Net weight	0.405 kg