

UT120 SERIES POCKET SIZE DIGITAL MULTIMETERS



UT120 series multimeters are designed for DIYers and electronics engineers to troubleshoot electronics systems development and electronics circuits. It is a simple and portable multimeter for every electronics engineer.



	Range	UT120A	UT120B	UT120C
DC voltage (V)	600V	±(0.8%+1)	±(0.8%+1)	±(0.8%+1)
AC voltage (V)	600V	±(1.2%+3)	±(1.2%+3)	±(1.2%+3)
DC current (A)	400mA			±(1%+3)
AC current (A)	400mA			±(1.5%+5)
Resistance (Ω)	40MΩ	±(1%+2)	±(1%+2)	±(1%+2)
Capacitance (F)	100μF		±(4%+3)	±(4%+3)
Frequency (Hz)	10MHz	±(0.5%+3)	±(0.5%+3)	±(0.5%+3)

Features

Display count		4000	4000	4000
Auto range		√	√	√
Duty cycle	0.1%~99.9%	√	√	√
Diode		√	√	√
Auto power off	Around 30 minutes	√	√	√
Continuity buzzer		√	√	√
Low battery indication	≤2.4V	√	√	√
Data hold		√	√	√
Relative mode		√	√	√
Input impedance for DCV	Around 10MΩ	√	√	√
Power	3V battery (CR2032)			
Display	43mm x 22mm			
Product color	Red and grey			
Product net weight	76g			
Product size	110mm x 58.2mm x 10.8mm			
Standard accessories	Battery, carrying case			
Standard individual packing	Blister, English manual			
Standard quantity per carton	60pcs			
Standard carton measurement	430mm x 255mm x 460mm			
Standard carton gross weight	11.5kg			