



MMX-4

Order No.: 0241070

PRODUCTINFOS

Miniature microphone mixer

- 4 mono microphone channels
- Output level control, peak LED
- Supplied w/o battery

Manufacturer information:

MONACOR INTERNATIONAL GmbH & Co. KG
Konsul-Smidt-Str. 68
28217 Bremen
Germany
info@monacor.com

Safety Notes and Warning Messages

The unit uses dangerous mains voltage. Leave servicing to skilled personnel only and do not insert anything into the air vents. Inexpert handling may result in electric shock.

Do not operate the unit and disconnect the mains plug from the socket immediately if the unit or the mains

cable is visibly damaged; if a defect might have occurred after the unit was dropped or suffered a similar accident, if malfunctions occur. In any case, the unit must be repaired by skilled personnel.

The unit is suitable for indoor use only. Protect it against dripping water and splash water, high air humidity and heat (admissible ambient temperature range: 0 - 40 °C).

Never pull the mains cable to disconnect the mains plug from the socket, always seize the plug.

If the unit is to be put out of operation permanently, take it to a local recycling plant for a disposal which is not harmful to the environment.

TECHNICAL SPECIFICATIONS

MMX-4

Input channels	4
Number of mix/mono	4
Mic input	5 mV, 4 x 6.3 mm jack
Master output	100 mV, 1 x 6.3 mm jack
Frequency range	20-20,000 Hz
THD	< 0.5%
S/N ratio	55 dB
Power supply	9 V battery or via optional power supply PSS-600E
Admiss. ambient temp.	0-40 °C
Dimensions	148 x 85 x 55 mm
Width	148 mm
Height	85 mm
Depth	55 mm
Weight	389 g
Packaging dimensions (W x H x L)	0.085 x 0.055 x 0.15 m
Gross weight	0.454 kg
Net weight	0.389 kg

MMX-4

EAN code	4007754014990
Net weight	0.389 kg