



GF-901

Order No.: 1001201

PRODUCTINFOS

Gooseneck condenser microphone,

for desktop microphone station transmitters.

- Balanced connection
- Supercardioid polar pattern
- LED for indicating operating status
- FI protection technology for suppressing external RF interference
- 3-pole XLR connection
- Total length: 310 mm

Please note: RELACART products are distributed by MONACOR INTERNATIONAL exclusively in the following countries: Germany, Austria, Switzerland, Netherlands, Belgium, Luxembourg, Denmark, Portugal, Malta. Orders from other countries cannot be fulfilled.

Manufacturer information:

Relacart Electronics Co., Ltd.
1408 Room, B Building

Fengxing Plaza
No. 242, Tianhe Road
Tianhe District
Guangzhou, Guangdong
China
info@relacart.com

Importer:

MONACOR INTERNATIONAL GmbH & Co. KG
Konsul-Smidt-Str. 68
28217 Bremen
Germany
info@monacor.com

TECHNICAL SPECIFICATIONS

GF-901

Description	gooseneck microphone
Transmission method	cable
Polar pattern	supercardioid
System	condenser
Audio frequency range	100-15,000 Hz
Nominal impedance	680 Ω
Sensitivity	7 mV/Pa
S/N ratio	> 55 dB
Max. sound pressure	110 dB
Power supply	DC 5 V
Admiss. ambient temp.	0-40 °C
Dimensions	310 mm
Weight	170 g
Connection	3-pole XLR
Packaging dimensions (W x H x L)	0.41 x 0.05 x 0.05 m
Gross weight	0.252 kg
Net weight	0.173 kg

GF-901

EAN code	4007754426618
Net weight	0.173 kg