



PA-1200IRD



Order No.: 1000829

PRODUCTINFOS

Internet radio DAB+/FM RDS tuner insertion with BT and USB interface

for PA mixing amplifiers with slot

- LAN or WLAN connection, WPS possible
- Detachable WLAN antenna
- Setup assistant for network
- FM tuner with RDS
- 30 presets for your favourites (Internet radio 10x, DAB+ 10x, FM 10x)
- App control with the UNDOK™ app
- BT connection
- USB storage media can be connected directly
- Media streaming from files shared on the network (UPnP server)
- Playback of MP3 and WAV files
- Display of the file name
- Simple folder navigation
- Alphanumeric LCD display
- Automatic switch-on after power failure (autostart)
- Storage of settings and operating modes
- Adjustable snooze function
- Alarm clock function

Manufacturer information:

MONACOR INTERNATIONAL GmbH & Co. KG
Konsul-Smidt-Str. 68
28217 Bremen
Germany
info@monacor.com

Safety and warning notices

Only use the device indoors and protect it from dripping and splashing water, high humidity and heat (permissible operating temperature range 0 - 40 °C).

Do not operate the appliance if there is visible damage to the appliance, if a defect is suspected after a fall or similar, or if malfunctions occur. Always return the appliance to a specialised workshop for repair.

If the appliance is to be taken out of service permanently, hand it over to a local recycling centre for environmentally friendly disposal.

TECHNICAL SPECIFICATIONS

PA-1200IRD

Description	internet radio, FM RDS and DAB+ tuner, USB player
Media	streaming, FM, DAB+, MP3, WAV, LAN/WLAN, BT, USB
Power supply	DC 17 V/500 mA
Mains voltage	DC 17 V
Admiss. ambient temp.	0-40 °C
Dimensions	195 x 40 x 135 mm
Weight	360 g
Connections	1 x RJ45 (LAN) 1 x IEC/coaxial plug for FM/DAB+ antenna 1 x SMA jack for WLAN antenna
Packaging dimensions (W x H x L)	0.22 x 0.175 x 0.06 m
Gross weight	0.565 kg

PA-1200IRD

EAN code	4007754418002
Net weight	0.46 kg