



## PA-1200DAB

Order No.: 1001513

### PRODUCTINFOS

#### DAB+/FM RDS tuner insertion with USB and SD interface

for PA mixing amplifiers with insertion slot

- DAB+ tuner
- FM tuner with RDS
- Bluetooth 5.0
- IR remote control
- USB storage media can be connected directly (SD and SDHC, 32 GB max.)
- USB 2.0 FAT16/FAT32
- Playback of MP3, WMA, WAV and FLAC files
- 30 station presets for FM
- 20 station presets for DAB+
- AUTO SCAN feature
- Alphanumerical LC display
- Display of file name/ID3 tag
- Removable DAB+ rod antenna
- Automatic switch-on after power loss (auto boot)
- Storage of settings

#### Manufacturer information:

MONACOR INTERNATIONAL GmbH & Co. KG  
Konsul-Smidt-Str. 68  
28217 Bremen  
Germany

info@monacor.com

### Safety and warning notices

Only use the device indoors and protect it from dripping and splashing water, high humidity and heat (permissible operating temperature range 0 - 40 °C).

Do not operate the appliance if there is visible damage to the appliance, if a defect is suspected after a fall or similar, or if malfunctions occur. Always return the appliance to a specialised workshop for repair.

If the appliance is to be taken out of service permanently, hand it over to a local recycling centre for environmentally friendly disposal.

## TECHNICAL SPECIFICATIONS

### PA-1200DAB

Description	DAB+ and FM RDS tuner, BT, USB player, SD
Media	DAB+, FM, USB, SD, SDHC, MMC, MP3, WMA, WAV, FLAC
Power supply	DC 17 V/180 mA (via amplifier)
Mains voltage	DC 17 V
Admiss. ambient temp.	0-40 °C
Dimensions	195 x 40 x 76 mm
Weight	328 g
Connections	1 x type f/coax jack for FM/DAB+ rod antenna 1 x 3.5 mm input (sym.)
Packaging dimensions (W x H x L)	0.12 x 0.08 x 0.22 m
Gross weight	0.7 kg

### PA-1200DAB

EAN code	4007754430431
Net weight	0.424 kg